

EP8000HSRE-RCD-V2 Portable Petrol Generator with E-Start

8 kVA Honda Powered Petrol Generator with RCD & E-Start

8 kVA Honda Powered Electric Start Generator complete with all the extras suitable for work site usage. Featuring RCD protected outlets and sturdy frame. The RCD earth leakage protected outlets are Work Safe approved and comply with Australian Standards.

Specifications

| | |
|--------------------------------------|---|
| Power Rating: | 8 kVA |
| Alternator Rating: | 8 kVA |
| Engine Model: | Honda GX390 |
| Phase: | 1 phase |
| Starting System: | Recoil/Electric |
| Fuel Tank Capacity: | 6.1 L |
| Noise Level @ 7m: | 72 dBA |
| Approx. Fuel Consumption @ 80% Load: | 2.58 L/Hr |
| Operation Hours @ 80% Load: | 2.36 hrs |
| Fuel Type: | Petrol |
| Volts: | 230 V |
| Outlets: | 2 x RCD Protected 15Amp, 1 x 32Amp Circuit Breaker |
| Dimensions: | 780 x 570 x 570 mm |
| Weight: | 95 kg |



**Specifications are subject to change without notice*

OPTIONAL EXTRA P/N: 10-GN-N3-32MM-008

Attach the optional wheels & handles kit designed specifically for this model and turn it into the ultimate trade generator.

