

EP8000HSRE-R/S-V2

## 8 kVA Honda Powered Petrol Generator with Remote Start

This is the Perfect Back up Generator for unreliable solar power. The controller on the 2-wire remote start kit will start the generator from the closure of a remote contact. This allows you to start your generator without going out to it.

### Specifications

|                                      |                    |
|--------------------------------------|--------------------|
| Power Rating:                        | 8 kVA              |
| Alternator Rating:                   | 9.5 kVA            |
| Engine Model:                        | Honda iGX390       |
| Phase:                               | 1 phase            |
| Starting System:                     | Recoil/Electric    |
| Fuel Tank Capacity:                  | 25 L               |
| Noise Level @ 7m:                    | 72 dBA             |
| Approx. Fuel Consumption @ 80% Load: | 2.58 L/Hr          |
| Operation Hours @ 80% Load:          | 9.7 hrs            |
| Fuel Type:                           | Petrol             |
| Volts:                               | 230 V              |
| Outlets:                             | 2 x 15Amp,         |
| Dimensions:                          | 780 x 570 x 570 mm |
| Weight:                              | 98 kg              |



*\*Specifications are subject to change without notice*

### OPTIONAL EXTRA P/N: 10-GN-N3-32MM-008

Raised wheel kit (2 x handles & 2 x wheels) for easy maneuvering. Suits 8kVA R/S-V2 and RCD models only.

