



Generators you can trust



1800 248 699



gentechgenerators.com.au

EP20000HSRE Portable Petrol Generator with E-Start

20 kVA Honda Powered Petrol Generator with E-Start

If you're in need of serious power for large power tools or backing up your house, then look no further! With EFI (**Electronic Fuel Injection**) for maximum fuel efficiency, enhanced reliability and improved start up. This massive generator comes standard with **long range fuel tank, battery, centre point lift, 2 x 32 Amp and 1 x 15 Amp outlets with circuit breaker.**

Specifications

Power Rating:	20 kVA
Alternator Rating:	20 kVA
Engine Model:	Honda iGX800 with Electronic Fuel Injection
Outlets:	2 x 32 Amp and 1 x 15 Amp 3 Pin outlets with circuit breaker
Phase:	1 phase
Starting System:	Electric Start
Fuel Tank Capacity:	34 L
Noise Level @ 7m:	75 dBA
Volts:	230 V
Approx. Fuel Consumption @ 80% Load:	6.88 L/Hr
Operation Hours @ 80% Load:	6.15 hrs
Fuel Type:	Petrol
Dimensions:	876 x 546 x 700 mm
Weight:	160 kg

**Specifications are subject to change without notice*



POWERED by
HONDA™

