

EP5900HSR Portable Petrol Generator

5.9 kVA Honda Powered Petrol Generator

This 5.9 kVA Generator is small but powerful, with 2 x 15 amp outlets, and Honda Australia Approved GX340 engine, this generator is perfect for the builder or tradie, running all your small power tools with ease.

Specifications

Power Rating:	5.9 kVA
Alternator Rating:	5.9 kVA
Engine Model:	Honda GX340
Phase:	1 phase
Starting System:	Recoil
Fuel Tank Capacity:	6.1 L
Noise Level @ 7m:	68 dBA
Outlets:	2 x 15 Amp
Volts:	230 V
Approx. Fuel Consumption @ 80% Load:	2.35 L/Hr
Operation Hours @ 80% Load:	2.6 hrs
Fuel Type:	Petrol
Dimensions:	735 x 545 x 545 mm
Weight:	70 kg



**Specifications are subject to change without notice*

POWERED by
HONDA

