

EP8000HSR Portable Petrol Generator

8 kVA Honda Powered Petrol Generator

This 8 kVA Generator is the perfect size for almost everything, with 2 x 15 amp outlets, and Honda Australia Approved GX390 engine, this generator will run your power tools, compressor, Welder and much more.

Specifications

Power Rating:	8 kVA
Alternator Rating:	9.5 kVA
Engine Model:	Honda GX390
Phase:	1 phase
Starting System:	Recoil
Fuel Tank Capacity:	6.1 L
Noise Level @ 7m:	74 dBA
Outlets:	2 x 15 Amp
Volts:	230 V
Approx. Fuel Consumption @ 80% Load:	2.58 L/Hr
Operation Hours @ 80% Load:	2.36 hrs
Fuel Type:	Petrol
Dimensions:	810 x 545 x 545 mm
Weight:	80 kg



**Specifications are subject to change without notice*

POWERED by
HONDA

