



gentechgenerators.com.au

Complete with generator, welder, compressor, and battery charger.

GENTECH WORKSTATIONS

Packed with a punch these workstations have everything you need.

Complete with 7kVA* generator, Welder, Compressor, and Battery charger, they really have it all.

Features of the Workstation			
Honda Petrol engine	Petrol models have reliable electric or recoil start GX390 Honda Australia approved engines, complete with Honda's 4 year warranty		
Yanmar Diesel Engine	Diesel models come with powerful and reliable Yanmar electric start engines		
NSM Alternator	With less than 6% harmonic distortion to run electronic equipment and tools		
Welder	160 or 200 amp at 60% duty cycle**		
Compressor	14CFM 50 L air compressor		
Battery Charger	10 Amp DC Battery charger		
Centre Point Lift	Makes lifting by crane or forklift easy		

^{*} Diesel units are 6.8kVA

^{**} Welder Amps depend on Petrol and diesel models see overleaf for detailed specs









Complete with generator, welder, compressor, and battery charger.

GENTECH WORKSTATIONS

Specifications

Model	WS200-14-10HSR	WS200-14-10-HSRE	WS160-14-10-YSRDE
Rated Voltage	230 V	230 V	230 V
Frequency	50 Hz	50 Hz	50 Hz
Rated Output	5600 Watts	5600 Watts	5440 Watts
Max. Output	7 kVA	7 kVA	6.8 kVA
Engine Type	Honda GX390	Honda GX390	Yanmar L100N5
Horsepower	11.7 HP	11 HP	11 HP
Starting System	Recoil	Recoil / Electric	Recoil / Electric
Size - LxWxH (mm)	900 x 870 x 680	900 x 870 x 680	900 x 870 x 680
Dry Weight	105 kg	110 kg	130 kg
Fuel Tank Capacity	6.1 L	6.1 L	5.4 L
Operating Hrs (80% Load)	2.5 Hours	2.5 Hours	3.3 Hours
Fuel Consumption (80% Load)	2.44 L/hr	2.44 L/hr	1.65 L/hr
Noise Level (7m)	69 dbA	69 dbA	69 dbA
Welder Duty Cycle	200 Amps @ 60%	200 Amps @ 60%	160 Amps @ 60%
Outlets	2 x 15 Amp	2 x 15 Amp	2 x 15 Amp
Air CompressorPressure	14 CFM	14 CFM	14 CFM
Air Compressor Capacity	50 L	50 L	50 L
Centre Point Lift	Yes	Yes	Yes
Battery Charger	Yes	Yes	Yes
Compressor	Yes	Yes	Yes
Brushless Alternator	Yes	Yes	Yes
Auto Decompressor	Yes	Yes	Yes

^{*}Specifications are subject to change without notice



